

# EXCB2-BBP-5

Units: mm

## Pin assign

BBCPCS	BBCPPS	Cable color	No.
GND	NC	Orange - Black1	1
NC	NC	Orange - Red1	26
GND	NC	Gray - Black1	2
NC	NC	Gray - Red1	27
GND	NC	White - Black1	3
NC	NC	White - Red1	28
GND	B7-	Yellow - Black1	4
B7	B7+	Yellow - Red1	29
GND	B6-	Pink - Black1	5
B6	B6+	Pink - Red1	30
GND	B5-	Orange - Black2	6
B5	B5+	Orange - Red2	31
GND	B4-	Gray - Black2	7
B4	B4+	Gray - Red2	32
GND	B3-	White - Black2	8
B3	B3+	White - Red2	33
GND	B2-	Yellow - Black2	9
B2	B2+	Yellow - Red2	34
GND	B1-	Pink - Black2	10
B1	B1+	Pink - Red2	35
GND	B0-	Orange - Black3	11
B0	B0+	Orange - Red3	36
GND	OFF7-	Gray - Black3	12
OFF7	OFF7+	Gray - Red3	37
GND	OFF6-	White - Black3	13
OFF6	OFF6+	White - Red3	38
GND	OFF5-	Yellow - Black3	14
OFF5	OFF5+	Yellow - Red3	39
GND	OFF4-	Pink - Black3	15
OFF4	OFF4+	Pink - Red3	40
GND	OFF3-	Orange - Black4	16
OFF3	OFF3+	Orange - Red4	41
GND	OFF2-	Gray - Black4	17
OFF2	OFF2+	Gray - Red4	42
GND	OFF1-	White - Black4	18
OFF1	OFF1+	White - Red4	43
GND	OFF0-	Yellow - Black4	19
OFF0	OFF0+	Yellow - Red4	44
GND	ERROUT-	Pink - Black4	20
ERROUT	ERROUT+	Pink - Red4	45
GND	EXT-	Orange - Continuous black line	21
EXT	EXT+	Orange - Continuous red line	46
GND	WR-	Gray - Continuous black line	22
WR	WR+	Gray - Continuous red line	47
GND	CS2-	White - Continuous black line	23
CS2	CS2+	White - Continuous red line	48
GND	CS1-	Yellow - Continuous black line	24
CS1	CS1+	Yellow - Continuous red line	49
GND	CS0-	Pink - Continuous black line	25
CS0	CS0+	Pink - Continuous red line	50

